

m/_{s²}

General purpose accelerometer

SPECIFICATIONS

786B-10


Sensitivity, ±10%, 25°C	100 mV/g
Acceleration range, VDC > 25 V	80 g peak
Amplitude nonlinearity	1%
	±5% 3 - 5,000 Hz :10% 1 - 9,000 Hz 3 dB 0.5 - 14,000 Hz
Resonance frequency	30 kHz
Transverse sensitivity, max	5% of axial
	25°C −10% 20°C +10%
Power requirement: Voltage source Current regulating diode	18 - 30 VDC 2 - 10 mA
10	5 kHz 700 μg 0 Hz 10 μg/√Hz 00 Hz 5 μg/√Hz 00 Hz 5 μg/√Hz
Output impedance	100 Ω
Bias output voltage	12 VDC
Grounding	case isolated, internally shielded
Temperature range	–50° to +120°C
Vibration limit	500 g peak
Shock limit	5,000 g peak
Electromagnetic sensitivity, equiv.	g, max 70 μg/gauss
Sealing	hermetic
Base strain sensitivity, max	0.0002 g/µstrain
Sensing element design	PZT, shear
Weight	90 grams
Case material	316L stainless steel
Mounting	1/4-28 UNF tapped hole
Mating connector	MIL-5015 style
Recommended cabling	J10 / J9T2A




Key features

• Long-lasting reliability at an affordable price

Manufactured in ISO 9001 facility





Connections	
Function	Connector pin
power/signal	A
common	В
ground	shell

Version | 10.2019

Accessories supplied: SF6 mounting stud (metric mounting available); calibration data (level 2)

CE

Note: Due to continuous process improvement, specifications are subject to change without notice. This document is cleared for public release.

The information provided herein is to the best of our knowledge true and accurate, it is provided for guidance only. All specifications are subject to change without prior notification. Althen – Your expert partner in Sensors & Controls | althensensors.com

Althen stands for pioneering measurement and custom sensor solutions. In addition we offer services such as calibration, design & engineering, training and renting of measurement equipment.

Germany/Austria/SwitzerlandBeneluxFranceSwedenUSA/CanadaOther countriesinfo@althen.desales@althen.nlinfo@althensensors.frinfo@althensensors.seinfo@althensensors.cominfo@althensensors.com