





SPECIFICATIONS

- Uniaxial
- MEMS Capacitive
- Measurement Range: ±2 to ±400 g
- Noise Density: 7 to 400 µg /√Hz
- Frequency Range (±5 %): DC to 2000 Hz
- Stainless-Steel Housing (IP68)
- Made in Germany



The key components in capacitive accelerometers are high-quality micro-electromechanical systems (MEMS) that feature excellent long-term stability and reliability. This technology enables the measurement of static (DC) and constant accelerations, which can be used to calculate the velocity and displacement of moving objects. Depending on the design of the spring-mass-damping system, however, it is also possible to detect dynamic (AC) accelerations with amplitudes up to ±400 q and within a frequency response range of up to 2 kHz (±5 %) or 4.2 kHz (±3 dB). Other advantages of capacitive accelerometers are their outstanding temperature stability, excellent response behavior and achievable resolution.

DESCRIPTION

The accelerometers of type ASC OS-115LN are based on proven MEMS technology and capacitive operating principle. The integrated electronic circuitry enables a differential analog voltage output (±4 V FSO) and flexible power supply voltage from 6 to 40 VDC. The LN (Low Noise) accelerometers from ASC provide an outstanding noise performance from 7 to 400 µg/√Hz which is essential for demanding measurements of smallest frequencies and amplitudes.

The sensors feature a robust, reliable stainless-steel housing with protection class IP68 and a detachable cable with configurable length and connectors.

The hermetically sealed housing of the accelerometers is ideal for very harsh environmental conditions, e.g. bogie stability tests and monitoring applications in rail transport or condition monitoring of vehicles and their components in the construction sector.



FEATURES


- Very Low Noise Differential Voltage Output
- DC Response, Gas damped
- High Shock Resistance
- Excellent Offset and Scale Factor Stability
- Detachable Connector Cable


OPTIONS

- Customized Cable Length
- **Customized Connector**
- TFDS Module
- V4A Stainless-Steel Housing

APPLICATIONS

- Railway Engineering
- Condition Monitoring
- Structural Health Monitoring









TYPICAL SPECIFICATIONS

_		
Dyr	חבו	nıc
U y ı	101	,,,,

Measurement Range	g	±2	±5	±10	±25	±50	±100	±200	±400
Scale Factor (sensitivity)	mV/g	2000	800	400	160	80	40	20	10
Noise Density	µg/√Hz	7	12	18	25	50	100	200	400
Specified Frequency Response Range (±5 %)	Hz	0 to 250	0 to 400	0 to 700	0 to 1300	0 to 1600	0 to 1700	0 to 1900	0 to 2000
Frequency Response Range (±3 dB)	Hz	0 to 525	0 to 800	0 to 1100	0 to 1750	0 to 2100	0 to 3000	0 to 3600	0 to 4200
Amplitude Non - Linearity	% FS0	<0.15 (typ) <0.5 (max)							
Transverse Sensitivity	%	<2 (typ) <3 (max)							

Electrical

Power Supply Voltage	V	6 to 40							
Operating Current Consumption	mA	<10							
Offset (bias)	m V	±80	±80	±40	±40	±40	±40	±40	±40
Broadband Noise (over specified frequency range ±5 %)	μV	225	195	190	145	160	165	175	180
Output Impedance	Ω	90							
Isolation		Case isolated							

Environmental

Temperature Coefficient of the Scale Factor (max)	ppm/K	±200							
Temperature Coefficient of the Offset (max)	mg/K	±0.8	±2	±4	±10	±20	±40	±80	±16 0
Operating Temperature Range	°C	Standard with Cable K1: -15 to +70 Optional with Cable K2: -55 to +1 25							
Storage Temperature Range	°C		-55 to +125						
Shock Limit (max peak)	g	2000	2000	5000	5000	5000	5000	5000	5000
Protection Class		IP68 Please note: the housing is bermetically sealed and therefore not renairable							

Physical

Sensing Element		MEMS Capacitive
Case Material		Stainless - Steel
Connector Sensor Housing		4-pin Comtronic (male)
Connector at Cable End		Optional
Mounting		Adhesive Screw Holes
Weight (without cable)	gram	31
Cable K1 (standard)		14 gram per meter AWG 30 Polyurethane (PUR) Diameter 3.05 mm waterproof
Cable K2 (optional)		15 gram per meter AWG 30 Fluorethylenpropylen (FEP) Diameter 2.75 mm waterproof





SENSOR CALIBRATION

Factory Calibration (supplied with the sensor)

Part Number									
Measurement Range (sensor)	9	±2	±5	±10	±25	±50	±100	±200	±400
Applied Frequency (min)	Hz	1	10	10	10	10	10	10	10
Applied Frequency (max)	Hz	100	400	700	1300	1600	1700	1900	2000
Input Amplitude	m/s²	5	5	50	100	200	200	200	200
Reference Frequency for Determination of Scale Factor	Hz	16	80	80	80	80	80	80	80

Calibration according DIN ISO 17025 (order separately)

Part Number									
Measurement Range (sensor)	g	±2	±5	±10	±25	±50	±100	±200	±400
Applied Frequency (min)	Hz	0.5	10	10	10	10	10	10	10
Applied Frequency (max)	Hz	150	800	1100	1750	2100	3000	3600	4200
Input Amplitude	m/s²	5	5	50	100	200	200	200	200
Reference Frequency for Determination of Scale Factor	Hz	16	80	80	80	80	80	80	80

Remarks:

- The conversion factor 1 g corresponds to 9.80665 m/s².
- If any other calibration procedure is required, don't hesitate to contact us. Our services include both factory calibration and calibration in accordance with DAkkS guidelines.
- Furthermore, s ensors have to be calibrated regularly to ensure accurate and precise results. On request we will be glad to remind you of the next scheduled calibration of your sensors.

Cable Code / Pin Configuration (4 Wire System)

	Pin	Color Code Cable Type K1	Color Code Cable Type K2	Description
1	Supply +	Blue	Red	Power supply voltage +6 to +40 VDC
2	Supply -	Brown	Black	Power GND
3	Signal +	Black	Green	Positive, analog output voltage signal for differential mode
4	Signal -	White	White	Negative, analog output voltage signal for differential mode





ORDERING INFORMATION

Series	Model	- Range [g] -	Cable Length [m]	Connector & Pinout	- Cable	
ASC OS	-115LN	002	6	А	K1	
		005			K2	
		010				
		025				
		050				
		100				
		200				
		400				

Example:

ASC OS-115LN-002-6A-K1

Ordering information are based on standard configurations. All customized versions regarding connector and/or pinout will lead to a corresponding product match code:

- Standard length of the integrated cable is 6 meter. However, different customized cable lengths are possible on request.
- Standard version has no connector at the cable end which is identified by "A" in the product match code. However, it is possible to ass emble almost all connector types during production.





SAFETY PRECAUTION FOR INSTALLING AND OPERATING

This data sheet is a part of the product. Read the data sheet carefully before using the product and keep it available for future operation. Handling, electrical connections, mounting or any other work performed at the sensor must be carried out by authorized experts only. Appropriate safety precautions must be taken to exclude any risk of personal injury and damage to operating equipment as a result of a sensor malfunction.

Handling

The sensor is packaged in a reliable housing to protect the sensing elements and integrated electronic components from the ambient environment. However, poor handling of the product can lead to damages that may not be visible and cause electrical failure or reliability issues. Handle the component with caution:

- Avoid shocks and impacts on the housing, such as dropping the sensor on hard surface
- Never move the sensor by pulling the cable
- Make sure that the sensor is used within the specified environmental conditions
- Transport and store the sensor in its original or similar packaging
- The sensor should be mounted on a stable flat surface with all screws tightened or other mounting options
- Avoid any deformation during mounting the sensor
- Mounting tolerances may have an influence on the measured result

Electrical

ASC's inertial sensors are working with many established data acquisition systems. However, make sure that a proper DAQ is used, for the corresponding operation principle of the sensor. Furthermore, suitable precautions shall be employed during all phases of shipment, handling and operating:

- Active sensor pins are susceptible to damage due to electrostatic discharge (ESD)
- Make sure that the sensor is used within the specified electrical conditions
- Check all electrical connect ions prior to initial setup of the sensor
- Completely shield the sensor and connecting cable
- Do not perform any electrical modifications at the sensor
- Do not perform any adaptions on the wiring or connectors while the device under power
- Never plug or unplugg the electrical connection while the sensor is under power
- When a certain pin is not used during operation, make sure that the pin is insulated

Quality

- We have a quality management system according to ISO 9001:2015.
- The Deutsche Akkreditierungsstelle GmbH (DAkkS) has awarded to our calibration laboratory the DIN EN ISO/IEC 17025:2018 accreditation for calibrations and has confirmed our competence to perform calibrations in the field of mec hanical acceleration measurements. The pictured DAkkS ILAC logo refers exclusively to the accredited service.
- All ASC products are (€ compliant.



Page 5/5

Version